POWER EQUIPMENT

2,100 WATT INVERTER GENERATOR

MODEL: BE2100I

WORKSHOP



FEATURES

- Ultralight and whisper quiet inverter that is easy to transport to bring power to the remotest locations.
- Produces clean energy that is needed for sensitive electronics like cell phones and computers.
- Rugged and reliable engine with automatic low oil-shutdown that safeguards the engine.
- Copper alternator windings increases efficiency and reduces heat build up to extend lifespan.
- Easy access outlets are protected by circuit breakers for safety.
- Sound dampening shell lowers volume and has easy access panels to keep maintenance simple.





Scan the QR code with your mobile device and discover more about this BE Inverter.







USB

DC 12V AC 120V PLUG TYPES

ENGINE

MODEL: POWEREASE 79CC

TYPE: AIR COOLED, 4-STROKE OHV

DISPLACEMENT: 79CC

DB RATING: 59dB @ 7M

ECONOMY MODE: ELECTRONIC

START TYPE: PULL START

FUEL TYPE: 86 OCTANE, UP TO 10% ETHANOL

FUEL TANK SIZE: 4.2L (1.1 GAL)
APPROX RUN TIME: 6HR @ 1/2 LOAD
OIL TYPE: SAE 10W30

CERTIFICATIONS: CSA, EPA III AND CALI CARB

FRAME

TYPE: ENCLOSED PLASTIC SHELL

PORTABILITY: CARRY HANDLE

ALTERNATOR

MAX WATT: 2,100 W
RUNNING WATT: 1,800 W
MASTER CIRCUIT BREAKER: 13.3A
VOLTAGES: 120V
WINDINGS: COPPER
HARMONIC DISTORTION: MAX 1.5%
GROUNDING: NEUTRAL BONDED

OUTLETS

2x USB PORTS 1x DC 12V@8.3A 2x 120V 20A HOUSEHOLD, NEMA 5-20R PARALLEL CAPABILITY

BOXED SIZE

LxWxH: 21" x 13" x 20"
WEIGHT: 53 LBS

UNIT SIZE



UNIT WEIGHT: 46 LBS

WARRANTY

ENGINE: 2 YEARS
ELECTRONICS: 1 YEAR
UPC: 777897293388